# Mars M1 Enhanced Firmware Updating Gu ide

# **1. Version Introduction**

Released date	Firmware Version	Version introduction	Download Link	Remark
25/1/2024	v2.0.2.4	• Initial Version	GoogleDrive cloud storage link: https://drive.google.co m/file/d/1NFALMa9X8 XdIXfAxj1U0QP- ffvKBtN8j/view? usp=drive_link	
12/4/2024	v2.0.4.5	<ul> <li>Fixed Known Issues</li> </ul>	https://download- hollyland.oss-us-east- 1.aliyuncs.com/Firmwa re/Video_transmissions /Mars_M1_Enhanced/ HLD_V9803Pro_H100_ S2.0.4.5_OTA_Commo n_20240412.zip	

# 2. Updating Guide

#### 2.1 Kindly Note:

- It takes the risk to to do the upgrade, please avoid updating during the important events;
- Please make sure the device with enough power during updating;
- Please don't unplug the USB flash disk during updating to avoid updating failure;

• Please feel free to contact us if the updating failure or error causes the malfunction: Hollyland Technical Support Engineer: <a href="mailto:support@hollyland-tech.com">support@hollyland-tech.com</a>

#### 2.2 Updating Tool

- Windows 10/11 PC
- USB-C Cable

## 2.3 Operation Steps

1.Format the USB flash disk into FAT32 format first, then place the updating file in the USB flash disk root directly.

	Format USB Drive	e (F:)	$\times$		
	Capacity:				
	7.49 GB		$\sim$		
	File system				
	FAT32 (Default)		~		
	Allocation unit size				
	4096 bytes		$\sim$		
	Restore device d	efaults			
	Volume label		_		
	Format options				
		Start Close	•		
File Home Share View					
	Aove Copy to	New item •	Properties	Select all Select none Invert selection	
Clipboard	Organize	New	Open	Select	
$\leftarrow$ $\rightarrow$ $\checkmark$ $\uparrow$ $\checkmark$ $\rightarrow$ This PC $\rightarrow$ USB Drive	e (H:)		v Ö	Search USB Drive (H	م (:
🔜 Desktop 🛷 ^ Name	^	Date modified	Туре	Size	
Downloads     HLD_F_TX_	H210_S2.1.0.3.ota	10/17/2022 10:35 AM	OTA File	40,390 KB	
<ul> <li>Documents</li> <li>Pictures</li> </ul>					

2. Insert the USB flash disk into the wireless monitor's Type-C port will the monitor enter the updating status automatically after 1 mins around. Then just waiting for the updating completion.

Notes: If you dont wanna wait, you can enter Device info: Click the Folder Icon to choose the OTA file to start the upgarding manually.

## 2.4 Special notes:

- If the USB flash disk which over 32G, the Window/Mac system don't have the FAT32 options, so need the professional disk software tools (like DiskGenius) to format it.
- The USB flash disk needs to be formatted into the FAT32 format first can the device recognize the USB flash disk.
- The updating file need to be placed in the USB flash disk root directory can the device read the updating file, the file can't be placed in other catalogue.
- Checking whether the monitor firmware version is the latest or not on the device information after the update is completed.